DARKGLASS ELECTRONICS OY
ELIMÄENKATU 20A, 2ND FLOOR
HELSINKI, FINLAND



MIDI Footswitch

Connections

MIDI IN: 5-pin DIN connector
· Connects to a MIDI OUT on another MIDI device
· Passes the MIDI messages through to MIDI OUT/THRU connector.

MIDI OUT/THRU: 7-pin DIN connector
· Connects to Darkglass amplifiers or pedals that have a MIDI IN connection.
· Also supports any generic MIDI device.
· Can simultaneously be used to power the MIDI footswitch from a Darkglass e500 or Combo Infinity amplifier.

USB: USB-C connector
· Connects to a computer for setting the configuration using Darkglass Suite
· Supports USB MIDI
· Can be directly connected to Darkglass e500 amplifier for syncing settings
· Can be used to power the MIDI footswitch from a power bank or a USB port or a USB charger

9V DC: Barrel jack connector (center negative)
· Can be used to power the MIDI footswitch.

DARKGLASS AMPLIFIER: ¼" TS jack connector
· Connects to FOOTSWITCH connector of Darkglass amplifiers.
· Works as a Darkglass Super Intelligent Footswitch.
· Can simultaneously be used to power the MIDI footswitch with a Darkglass amplifier.

Controls

· 5 footswitch buttons with RGB LED indicators.

Functions

· Freely configurable via the Darkglass Suite software (MIDI PC & CC commands).
· Ready configurations for Darkglass products available on the Darkglass Suite.
· Supports 5 banks with 5 presets each in "bank mode".
· Can be powered from 9V DC, USB, MIDI OUT/THRU or DARKGLASS AMPLIFIER connector.

Commercial information

MSRP: 210 EUR

Dimensions Unpacked: Width 276 mm (10.8 in) Height 54 mm (2.1 in) Depth 54.6 mm (2.1 in)

Hi-Res Images:
https://mega.nz/folder/DqolwTLC#P9Zzs349TSQIQYPUFTdmmw