

OMNITRONIC PM-202F 2-Channel DJ Mixer with Filter and Bluetooth

DJ mixer with Bluetooth connectivity and sound filter

Art. No.: 10006863

GTIN: 4026397731071



List price: 189.21 €

incl. 19% VAT.

Features:

- Bluetooth signal routable to channel 1 and 2
- DJ filter LPF/HPF bipolar per channel
- DJ microphone channel with level control and 2-band equalizer
- Crossfader with adjustable curve and reverse function
- Master channel with level control and stereo LED level meter
- 4 line and 2 phono inputs via RCA jacks
- Additional recording output
- Pre-fader listening to all input channels and the master output via adjustable stereo headphones output
- Control via Bluetooth
- Bluetooth: operating range up to 15m
- Desktop console housing
- For application areas such as: Party room; mobile use; mobile djs / entertainer
- The article is delivered ready to stand
- Various versions available

Logistic

EAN / GTIN: 4026397731071

Weight: 2,75 kg

Length: 0.36 m

Width: 0.25 m

Height: 0.15 m

Technical specifications:

Power supply: 100-240 V AC, 50/60 Hz

Power consumption: Max. 8 W

Protection class: Protection class II

Power connection:	Mains input via C8 (M) "figure 8" mounting version power supply cord with Euro plug (provided)
Frequency range:	20 - 20000 Hz
S/N ratio:	>80 dB
THD:	<0.1 % at 1 kHz
DJ filter:	Per channel: LPF/HPF bipolar,
Control:	Bluetooth
Bluetooth:	Version: 4.2 + EDR Profiles: A2DP, AVRCP
Bluetooth device name:	PM-202F
Range:	Bluetooth: up to 15m
Crosstalk:	>60 dB
Control elements:	Crossfader, Crossfade curve control, crossfade reverse switch, FX Parameter control, power switch
Status LED:	Power, master level meter, CUE, pairing
Connections:	Input: line/phono via 2 x stereo RCA Input: line via 2 x stereo RCA Input: microphone via 1 x 3-pin XLR (F) mounting version Input: antenna via 1 x SMA (F) mounting version Input: Earthing connection via 2 x screw terminal Output: master via 2 x 3-pin XLR (M) mounting version Output: master via 1 x stereo RCA Output: rec. via 1 x stereo RCA Output: headphones via 1 x 6.3 mm jack socket (stereo) mounting version Output: headphones via 1 x 3.5 mm jack (stereo) mounting version
Channels:	Input channel: 2 x stereo with Line-Line/Phono-Bluetooth switch via RCA, channel control via 60mm fader, 2-band tone control EQ, gain control, CUE switch Microphone channel: 1 x mono via XLR, channel control via rotary dial, 2-band tone control EQ Master output: 1 x stereo via XLR or RCA, channel control via rotary dial, balancecontrol Headphones output: stereo via jack, channel control via rotary dial, cue mix function Rec. output: stereo via RCA
Material:	Metal
Color:	Black, matte
Housing design:	Desktop console housing
Dimensions:	Length: 30.5 cm Width: 19.0 cm Height: 11.0 cm
Weight:	2.15 kg
Weight:	1.97 kg
Cable length:	2.10 m detachable 2.10 m detachable
Weight:	0.96 kg

Carrier frequency:	2.4 GHz
Weight:	0.005 kg
Weight:	0.46 kg

Scope of delivery:

- 1 x mixer
- 1 x power cord
- 1 x antenna
- 1 x RCA cable
- 1 x user manual
- 1 x declaration of conformity